


How to Program an ATtiny85 with an Arduino Uno

What is an ATtiny85?

ATtiny85 is a 8-bit AVR microcontroller based on AVR enhanced RISC architecture. It has an 8-pin interface (PDIP) and comes in the category of low-power microcontrollers. This microcontroller is designed and manufactured by Microchip. [Know More](#)



Set the Arduino Uno Into ISP Mode


So that the Arduino can act as a device to upload code to ATtiny85. `File - Examples - Arduino ISP - ArduinoISP`

Add this line `#define USE_OLD_STYLE_WIRING` to the code before `setup()`

UPLOAD!

Wiring

The pins are not labelled so you will have to refer to the pinout.



Arduino --> ATtiny85

1. 5V --> Vcc (8)
2. GND --> GND (4)
3. Pin 13 --> Pin 2 (7)
4. Pin 12 --> Pin 1 (6)
5. Pin 11 --> Pin 0 (5)
6. Pin 10 --> Reset (1)

Only when you are uploading code to ATtiny85

Put a 10uF capacitor between GND and RESET on Arduino


Adding Attiny85 to Boards Manager

We have to make ATtiny compatible with Arduino IDE first, so that we can choose ATtiny85 from


Tools -> Board Go to Arduino Preference

Copy the below code and paste it into Additional Boards Manager URLs, if you already have a board manager URL just add a comma before pasting. Click OK and restart Arduino IDE.

https://raw.githubusercontent.com/damellis/attiny/ide-1.6.x-boards-manager/package_damellis_attiny_index.json




Go to **Tools - Board - Boards Manager**, search for ATtiny, then install!



Get Started

Before uploading the code, we have to change some settings.

1. Tools -> Board scroll to the bottom select ATtiny25/45/85
2. Tools -> Processor--> 8 MHz (internal)
3. Tools-->Programmer-->Arduino as ISP
4. Check that all wiring, capacitor, and board selections are correct.



Open up a basic code and upload as usual! If it doesn't work, try `Tools - Burn Bootloader`

Revision #2

Created 21 November 2023 10:11:25 by Joanne Leung

Updated 21 November 2023 11:02:42 by Joanne Leung